

Pump type: Submersible pump
 Application: Waste water, sewage

Pump data

Solids passage: 100 mm
 Discharge/ Suction diameter: NW100 / NW125, PN10
 Impeller type: closed screw
 Impeller diameter: 210 - 250 mm
 Recommended min. flow: 6 l/sec (21 m3/h)
 Weight: 130 kg

Motor

Mains: 50 c/s – 3 phase
 Rated shaft power: 4.0 kW
 Rated electrical power: 5.3 kW
 Nominal speed: 930 rpm
 Motor efficiency: 75%
 Power factor (cos phi): 0.75
 Degree of protection: IP 68
 Isolation class: F (155°C)
 Max. water temperature: 40°C
 Standard cable length: 10 m

Materials

Pump casing: Cast iron GG 25 (EN-GJL-250)
 Impeller: S.g cast iron GGG 40 (EN-GJS-400-15)
 Motor unit: Cast iron GG 25 (EN-GJL-250)
 Shaft: AISI 431
 Bolts: Alt: AISI 316
 Elastomers: AISI 316
 Nitrile (NBR) or Neoprene (CR)
 Viton (FPM)
 Neoprene (CR)
 Electrical cable: Neoprene (CR)
 Seal lubrication: Oil
 Seal pump side: Silicon carbide – Silicon carbide - FPM
 Seal motor side: Carbon – Ceramic - NBR
 Coating: Two components Polyurethane

Installation options

Header coupling: BWK 100
 Guide bar coupling: OWK 100-N
 Freestanding: 100mm hose connection
 Including support (VRS): G 4" threaded connection
 Dry Installation: vertical or horizontal install.
 Including cooling system (ODO): discharge flange NW100
 suction flange NW125



Optional

- Flameproof version, to class: II 2 G Ex d IIB c T4
 Standard: II 2 G Ex b c d IIB T4 Gb
 With Frequency control: II 2 G Ex b c d IIB T3 Gb
- Thermo switches in stator windings
- Cable protective sheathing (AISI 316)
- Water detector in motor and oil chamber

Connections

voltage [V]*	current [A]	Electrical cable size [mm2]		motor protection and/or water detector		flameproof version		
		direct start	stardelta start	direct start	stardelta start	direct start	stardelta start	
230	17.9	4G2.5	7G1.5	7G2.5	12G1.5	7G2.5	12G1.5	
400	10.3	4G2.5	7G1.5	7G1.5	12G1.5	7G1.5	12G1.5	
500	8.2	4G2.5	7G1.5	7G1.5	12G1.5	7G1.5	12G1.5	
starting current DOL start : 5.5 x rated current								
starting current YD start : 1.8 x rated current								
							* other voltages on request	

